

On Robust Stability of Multivariable Interval Control Systems

Zhizhen Wang^(1,2) Long Wang⁽³⁾ Wensheng Yu⁽²⁾ Guoping Liu^(2,4)

(1) Shanghai Normal University, Shanghai, 200234, CHINA

(2) Laboratory of Complex Systems and Intelligence Science, Institute of Automation,
Chinese Academy of Sciences, Beijing, 100080, CHINA

(3) Center for Systems and Control, Department of Mechanics and Engineering Science,
Peking University, Beijing, 100871, CHINA

(4) School of Mechanical, Materials, Manufacturing Engineering and Management,
University of Nottingham, United Kingdom

Abstract: This paper studies robustness of MIMO control systems with parametric uncertainties, and establishes a lower dimensional robust stability criterion. For control systems with interval transfer matrices, we identify the minimal testing set whose stability can guarantee the stability of the entire uncertain set. Our results improve the results in the literature, and provide a constructive solution to the robustness of a family of MIMO control systems.

Keywords: Robust Stability, Multivariable Feedback Systems, Polynomial Matrices, Interval Polynomials, Edge Theorem.

1 Introduction

Robustness is considered as an elementary property in the analysis and design of control systems. A control system is said to be robust if it retains an assigned degree of stability or performance under perturbations. Robust control under structured perturbations has been an active research area in recent years^{[1]–[11]}.

Robust stability problem for control systems with interval characteristic polynomials was initiated by Kharitonov(1978)^[1], who showed that the Hurwitz stability of a real interval polynomial family can be guaranteed by the Hurwitz stability of four prescribed critical vertex polynomials in this family. Bartlett, Hollot and Huang extended the result and presented the Edge Theorem^[2], which says that the stability of a polytope of polynomials can be guaranteed by the stability of its one-dimensional exposed edge polynomials. Chapellat et al.(1989)^[3] refined the Kharitonov's Theorem, and proved that the robust stability of the unity feedback control system family with an interval plant and a fixed controller in forward path can be guaranteed by the stability of 32 prescribed one-dimensional unity feedback control systems in this family.

When considering multivariable control systems, the robust stability problem becomes more complicated and challenging^{[4]–[9]}. For Hurwitz stability of interval matrices, Bialas 'proved' that in order to guarantee robust stability, it suffices to check all vertex matrices^[4]. Later, it was shown by Barmish that Bialas's result was incorrect^[5]. Kokame and Mori established a Kharitonov-like result on robust Hurwitz stability of interval polynomial matrices^[6]. Their result is refined by Wang, Wang and Yu^[7]. Kamal and Dahleh established some robust stability criteria for MIMO control systems with fixed controllers and uncertain plant^[8].

In this paper, we focus on a class of MIMO feedback control systems with their transfer function matrices described by

$$\mathcal{M}(s) = \mathcal{B}(s)A(s) + \mathcal{D}(s)C(s) \quad (1)$$

$$\mathcal{B}_{ij}(s) = \left\{ b_{ij}^{(0)} + b_{ij}^{(1)}s + \cdots + b_{ij}^{(n)}s^n, \quad b_{ij}^{(k)} \in [\underline{b}_{ij}^{(k)}, \bar{b}_{ij}^{(k)}] \right\} \quad (2)$$

$$\mathcal{D}_{ij}(s) = \left\{ d_{ij}^{(0)} + d_{ij}^{(1)}s + \cdots + d_{ij}^{(n)}s^n, \quad d_{ij}^{(k)} \in [\underline{d}_{ij}^{(k)}, \bar{d}_{ij}^{(k)}] \right\} \quad (3)$$

$$\mathcal{B}(s) = \left\{ (b_{ij}(s))_{n \times n}, \quad b_{ij}(s) \in \mathcal{B}_{ij}(s) \right\} \quad (4)$$

$$\mathcal{D}(s) = \left\{ (d_{ij}(s))_{n \times n}, \quad d_{ij}(s) \in \mathcal{D}_{ij}(s) \right\} \quad (5)$$

where n is a given positive integer, and $\underline{b}_{ij}^{(k)}, \bar{b}_{ij}^{(k)}, \underline{d}_{ij}^{(k)}, \bar{d}_{ij}^{(k)}$ are given real numbers. And $A(s) = (a_{ij}(s))_{n \times n}$, $C(s) = (c_{ij}(s))_{n \times n}$ are two fixed polynomial matrices, $\mathcal{B}(s), \mathcal{D}(s)$ are interval polynomial matrices and $\mathcal{B}_{ij}(s), \mathcal{D}_{ij}(s)$ are interval polynomials, where $A(s) = (a_{ij}(s))_{n \times n}$ means that the matrix is an $n \times n$ one and its ij -th entry is $a_{ij}(s)$. Rewrite $\mathcal{M}(s)$ as

$$\mathcal{M}(s) = M_n s^n + M_{n-1} s^{n-1} + \cdots + M_0$$

where M_i is an $n \times n$ scalar matrix.

Assumption A: $\det(M_n) \neq 0$ over $\mathcal{M}(s)$.

In the sequel, we study the multivariable interval control system whose characteristic polynomial matrix $\mathcal{M}(s)$ satisfies Assumption A. By exploiting the uncertainty structures, we are able to reduce the computational burden in checking robust stability.

An outline of the paper is as follows. Some useful definitions and lemmas are presented in Section 2. Section 3 contains our main result on minimal dimension robust stability criterion. An example is worked out in Section 4, and some discussions are made in Section 5. Concluding remarks are given in Section 6.

2 Preliminaries

Definition 2.1 Given an interval polynomial set $\mathcal{R}(s) = \sum_{i=0}^m r_i s^i$, $r_i \in [r_i^L, r_i^U]$, its Kharitonov vertex set is defined as $\mathcal{R}^V(s) = \{r_1(s), r_2(s), r_3(s), r_4(s)\}$, and its Kharitonov edge set is defined as $\mathcal{R}^E(s) = \{\lambda r_i(s) + (1 - \lambda)r_j(s), (i, j) \in \{(1, 2), (2, 4), (4, 3), (3, 1)\}, \lambda \in [0, 1]\}$, where

$$\begin{aligned} r_1(s) &= r_0^L + r_1^L s + r_2^U s^2 + r_3^U s^3 + r_4^L s^4 + \cdots \\ r_2(s) &= r_0^L + r_1^U s + r_2^U s^2 + r_3^L s^3 + r_4^L s^4 + \cdots \\ r_3(s) &= r_0^U + r_1^L s + r_2^L s^2 + r_3^U s^3 + r_4^U s^4 + \cdots \\ r_4(s) &= r_0^U + r_1^U s + r_2^L s^2 + r_3^L s^3 + r_4^U s^4 + \cdots \end{aligned}$$

Denote the Kharitonov vertex sets and the Kharitonov edge sets of $\mathcal{B}_{ij}(s), \mathcal{D}_{ij}(s)$ as $\mathcal{B}_{ij}^V(s), \mathcal{D}_{ij}^V(s), \mathcal{B}_{ij}^E(s)$ and $\mathcal{D}_{ij}^E(s)$, respectively.

Definition 2.2 A fix polynomial is said to be (Hurwitz) stable if all its roots lie in the strict left half of the complex plane. A polynomial matrix is said to be stable if its determinant is stable.

Lemma 1 (Edge Theorem^[2]) Let Ω be a polytope of polynomials without degree dropping. Then the boundary of $R(\Omega)$ is contained in the root space of the exposed edges of Ω , where $R(W) = \{s \text{ such that } T(s) = 0 \text{ for some polynomial } T \in W\}$ is called the root space of W .

Lemma 2 $A(s)$ and $C(s)$ are defined as before. Let $B(s) = (b_{ij}(s))_{n \times n}$, $D(s) = (d_{ij}(s))_{n \times n}$ and

$$N^{(i)}(s) = \left\{ B(s)A(s) + D(s)C(s) : \begin{array}{l} \exists k_1, k_2 \in \{1, \dots, n\}; \quad l = 1, \dots, n \\ b_{ik_1}(s) \in \mathcal{B}_{ik_1}^E(s), \quad b_{il}(s) \in \mathcal{B}_{il}^V(s), \quad l \neq k_1; \\ d_{ik_2}(s) \in \mathcal{D}_{ik_2}^E(s), \quad d_{il}(s) \in \mathcal{D}_{il}^V(s), \quad l \neq k_2 \end{array} \right\} \quad (6)$$

$$N_E^{(i)}(s) = \left\{ \begin{array}{l} \exists k \in \{1, \dots, n\}; \quad l \neq k, \quad l = 1, \dots, n \\ B(s)A(s) + D(s)C(s) : \quad \begin{array}{l} b_{ik}(s) \times d_{ik}(s) \in \left(\mathcal{B}_{ik}^E(s) \times \mathcal{D}_{ik}^V(s) \right) \cup \left(\mathcal{B}_{ik}^V(s) \times \mathcal{D}_{ik}^E(s) \right) \\ b_{il}(s) \times d_{il}(s) \in \left(\mathcal{B}_{il}^V(s) \times \mathcal{D}_{il}^V(s) \right) \end{array} \end{array} \right\} \quad (7)$$

Then, $N^{(i)}(s)$ is stable for all $i \in \{1, \dots, n\}$ if and only if $N_E^{(i)}(s)$ is stable.

Proof (Sufficiency) Suppose that $N_E^{(i)}(s)$ is stable, our aim is to prove that $N^{(i)}(s)$ is stable. For any $N(s) \in N^{(i)}(s)$, there exist $k_1, k_2 \in \{1, \dots, n\}$ such that

$$\begin{array}{ll} b_{ik_1}(s) \in \mathcal{B}_{ik_1}^E(s); & b_{il}(s) \in \mathcal{B}_{il}^V(s), \quad l \neq k_1, l = 1, \dots, n \\ d_{ik_2}(s) \in \mathcal{D}_{ik_2}^E(s); & d_{il}(s) \in \mathcal{D}_{il}^V(s), \quad l \neq k_2, l = 1, \dots, n \end{array} \quad (8)$$

$$N(s) = \begin{pmatrix} \sum_k \left(b_{1k}(s)a_{k1}(s) + d_{1k}(s)c_{k1}(s) \right) & \cdots & \sum_k \left(b_{1k}(s)a_{kn}(s) + d_{1k}(s)c_{kn}(s) \right) \\ \vdots & \ddots & \vdots \\ \sum_k \left(b_{ik}(s)a_{k1}(s) + d_{ik}(s)c_{k1}(s) \right) & \cdots & \sum_k \left(b_{ik}(s)a_{kn}(s) + d_{ik}(s)c_{kn}(s) \right) \\ \vdots & \ddots & \vdots \\ \sum_k \left(b_{nk}(s)a_{k1}(s) + d_{nk}(s)c_{k1}(s) \right) & \cdots & \sum_k \left(b_{nk}(s)a_{kn}(s) + d_{nk}(s)c_{kn}(s) \right) \end{pmatrix} \quad (9)$$

By definition, $N(s)$ is stable if and only if $\det N(s)$ is stable. By Laplace formula, expanding the determinant along the i -th row, we have

$$\det N(s) = \sum_k (b_{ik}(s)a_{k1}(s) + d_{ik}(s)c_{k1}(s)) N_{i1} + \cdots + \sum_k (b_{ik}(s)a_{kn}(s) + d_{ik}(s)c_{kn}(s)) N_{in},$$

where N_{ij} is the algebraic complementary minor of the ij -th entry of $N(s)$, which is independent of $b_{i1}(s), \dots, b_{in}(s), d_{i1}(s), \dots, d_{in}(s)$. By a simple algebraic manipulation, we have

$$\begin{aligned} \det N(s) &= \sum_{j=1}^n b_{ij}(s) (\sum_{k=1}^n a_{jk}(s) N_{ik}) + \sum_{j=1}^n d_{ij}(s) (\sum_{k=1}^n c_{jk}(s) N_{ik}) \\ &= b_{ik_1}(s) \delta_1(s) + d_{ik_2}(s) \delta_2(s) + \delta_3(s) \end{aligned}$$

where $\delta_l(s)$ is a term which is independent of $b_{ik_1}(s), d_{ik_2}(s)$. Denote

$$\left\{ \begin{array}{l} b_{ik_1}(s) \times d_{ik_2}(s) \in \left(\left(\mathcal{B}_{ik_1}^E(s) \times \mathcal{D}_{ik_2}^V(s) \right) \cup \left(\mathcal{B}_{ik_1}^V(s) \times \mathcal{D}_{ik_2}^E(s) \right) \right) \\ b_{il}(s) \in \mathcal{B}_{il}^V(s), \quad l \neq k_1, \quad l = 1, \dots, n \\ d_{il}(s) \in \mathcal{D}_{il}^V(s), \quad l \neq k_2, \quad l = 1, \dots, n \end{array} \right\} \quad (10)$$

By Lemma 1, the stability of each such polytope is equivalent to the stability of its exposed edges. These edges are obtained by letting $B(s)$ and $D(s)$ satisfy (10). Thus, $\det N(s)$ is stable for $N(s)$ satisfying (8),(9) if and only if $\det N(s)$ is stable for $N(s)$ satisfying (9),(10). Since $N_E^{(i)}(s)$ is stable, this shows that $N(s)$ is stable. Hence, sufficiency is proved.

(Necessary) This is obvious since $N_E^{(i)}(s) \subset N^{(i)}(s)$.

3 Robust Stability Criterion

In this section, we consider the uncertain system family (1). Before presenting our main result, we first define some notations. The notation $X \times Y$ stands for the Cartesian product, which is the set of all ordered pairs (x, y) , where $x \in X, y \in Y$. Let S_n denote the set of all bijections of the set $\{1, \dots, n\}$

onto itself, and T_n be the set of all functions from the set $\{1, \dots, n\}$ onto itself. Take

$$\begin{aligned}\mathcal{B}_E(s) &= \left\{ B(s) \in \mathcal{B}(s) : \begin{array}{l} b_{ij}(s) \in \mathcal{B}_{ij}^E(s), j = \sigma(i) \\ b_{ij}(s) \in \mathcal{B}_{ij}^V(s), j \neq \sigma(i) \end{array}, \sigma \in S_n \right\} \\ \mathcal{D}_E(s) &= \left\{ D(s) \in \mathcal{D}(s) : \begin{array}{l} d_{ij}(s) \in \mathcal{D}_{ij}^E(s), j = \sigma(i) \\ d_{ij}(s) \in \mathcal{D}_{ij}^V(s), j \neq \sigma(i) \end{array}, \sigma \in S_n \right\} \\ \mathcal{B}_E \mathcal{D}_E &= \mathcal{B}_E(s) \times \mathcal{D}_E(s) \\ \mathcal{BD} &= \left\{ \begin{array}{l} B(s) \times D(s) \\ \in \mathcal{B}_E \mathcal{D}_E \end{array} : \begin{array}{l} \eta \in T_n \\ b_{ij}(s) \times d_{ij}(s) \in \left(\mathcal{B}_{ij}^E(s) \times \mathcal{D}_{ij}^V(s) \right) \cup \left(\mathcal{B}_{ij}^V(s) \times \mathcal{D}_{ij}^E(s) \right), j = \eta(i); \\ b_{ij}(s) \times d_{ij}(s) \in \mathcal{B}_{ij}^V(s) \times \mathcal{D}_{ij}^V(s), j \neq \eta(i) \end{array} \right\}\end{aligned}$$

The following theorem was given by Kamal and Dahleh (1996).

Proposition 1^[8] $\mathcal{M}(s)$ is stable for all $B(s) \in \mathcal{B}(s), D(s) \in \mathcal{D}(s)$ if and only if $\mathcal{M}(s)$ is stable for all $B(s) \times D(s) \in \mathcal{B}_E \mathcal{D}_E$.

As a generalization of the Generalized Kharitonov Theorem, Proposition 1 addresses the robust stability of $\mathcal{M}(s)$ and reduces it to $4^{2n^2}(n!)^2$ robust stability problems involving $2n$ uncertain parameters. In this paper, we will show that, by further making use of the uncertainty structure information, the original robust stability problem can be reduced to $(2n)!4^{2n^2}(n!)$ robust stability problems involving n uncertain parameters. By Proposition 1 and Lemma 2, we get the main result of this paper.

Theorem 1 $\mathcal{M}(s)$ is stable for all $B(s) \in \mathcal{B}(s), D(s) \in \mathcal{D}(s)$ if and only if $\mathcal{M}(s)$ is stable for all $B(s) \times D(s) \in \mathcal{BD}$.

Proof: By Proposition 1, $\mathcal{M}(s)$ is stable for all $B(s) \in \mathcal{B}(s), D(s) \in \mathcal{D}(s)$ if and only if $\mathcal{M}(s)$ is stable for all $B(s) \times D(s) \in \mathcal{B}_E \mathcal{D}_E$. For any $n(s) \in \mathcal{M}(s)$ with $B(s) \times D(s) \in \mathcal{B}_E \mathcal{D}_E$, fixing the rows from the second to the n -th rows and applying Lemma 2 to the first row, we have

$$\mathcal{M}(s) \text{ is stable for all } B(s) \in \mathcal{B}(s), D(s) \in \mathcal{D}(s)$$

if and only if

$$\mathcal{M}(s) \text{ is stable for all } B(s) \times D(s) \in \mathcal{BD}_1 \cap \mathcal{B}_E \mathcal{D}_E$$

where $\mathcal{BD}_1 \subset \mathcal{B}(s) \times \mathcal{D}(s)$ satisfies (10) when $i = 1$. Repeating the procedure for the remaining rows consecutively, we get the conclusions.

Remark 1 Theorem 1 shows that, the criterion for the robust stability of interval polynomial matrices can be greatly simplified. Proposition 1 of Kamal and Dahleh, reduced the $2n^2$ -dimensional stability verification problem to $2n$ -dimensional problem, and our result reduces the $2n^2$ -dimensional stability verification problem to n -dimensional one.

Remark 2 Theorem 1 establishes a minimal dimension testing criterion for robust stability of multivariable control systems. By making use of the uncertainty information of $\mathcal{B}(s)$ and $\mathcal{D}(s)$, i.e., not only making use of the uncertainty structure information in $\mathcal{B}(s)$ and $\mathcal{D}(s)$ separately (this is exactly what Kamal and Dehleh did), but also making use of the uncertainty structure information collectively, we are able to improve the robust stability results given by Kamal and Dehleh.

Remark 3 Theorem 1 allows us to improve the main results of Kamal and Dehleh.

4 Illustrative Example

Recall the two-link planar manipulator considered by Kamal and Dehleh. The characteristic polynomial of the closed loop system is

$$T(\epsilon) = \det \left(M(\theta_d)s^3 + K_d s^2 + K_p s + K_r \right) \quad (11)$$

where $\theta_d \in [0, \pi/2]$ is the joint angle and

$$\begin{aligned}
M(\theta_d) &= \begin{pmatrix} 3 + 2\cos(\theta_d) & 1 + \cos(\theta_d) \\ 1 + \cos(\theta_d) & 1 \end{pmatrix} \\
K_d &= \begin{pmatrix} k_{d11} & k_{d12} \\ k_{d21} & k_{d22} \end{pmatrix} \\
K_p &= \begin{pmatrix} k_{p11} & k_{p12} \\ k_{p21} & k_{p22} \end{pmatrix} \\
K_r &= \begin{pmatrix} k_{r11} & k_{r12} \\ k_{r21} & k_{r22} \end{pmatrix} \\
\begin{aligned}
k_{d11} &\in [6.07 - 6.07\epsilon, 6.07 + 6.07\epsilon], & k_{d12} &\in [2.22 - 2.22\epsilon, 2.22 + 2.22\epsilon] \\
k_{d21} &\in [2.22 - 2.22\epsilon, 2.22 + 2.22\epsilon], & k_{d22} &\in [1.62 - 1.62\epsilon, 1.62 + 1.62\epsilon] \\
k_{p11} &\in [6.12 - 6.12\epsilon, 6.12 + 6.12\epsilon], & k_{p12} &\in [2.24 - 2.24\epsilon, 2.24 + 2.24\epsilon] \\
k_{p21} &\in [2.24 - 2.24\epsilon, 2.24 + 2.24\epsilon], & k_{p22} &\in [1.64 - 1.64\epsilon, 1.64 + 1.64\epsilon] \\
k_{r11} &\in [5.11 - 5.11\epsilon, 5.11 + 5.11\epsilon], & k_{r12} &\in [1.87 - 1.87\epsilon, 1.87 + 1.87\epsilon] \\
k_{r21} &\in [1.87 - 1.87\epsilon, 1.87 + 1.87\epsilon], & k_{r22} &\in [1.37 - 1.37\epsilon, 1.37 + 1.37\epsilon]
\end{aligned}
\end{aligned} \tag{12}$$

Since for any fixed $\theta_d \in [0, \pi/2]$, the inertia matrix

$$M(\theta_d) = \begin{pmatrix} 1 & (1 + \cos(\theta_d)) \\ (-1 + \cos(\theta_d)) & 1 \end{pmatrix} \begin{pmatrix} 1 & 0 \\ 2 & 1 \end{pmatrix}$$

In what follows, we take the uncertain inertia matrix as

$$M(s) = B(s)A(s)$$

where $A(s) = \begin{pmatrix} 1 & 0 \\ 2 & 1 \end{pmatrix}$ and

$$\begin{aligned}
B(s) \in \mathcal{B}(s) &= \{(b_{ij}(s))_{2 \times 2} : b_{ij}(s) \in \mathcal{B}_{ij}(s)\} \\
\mathcal{B}_{11}(s) &= s^3, \quad \mathcal{B}_{12}(s) = b_{12}s^3, \quad b_{12} \in [1, 2] \\
\mathcal{B}_{22}(s) &= s^3, \quad \mathcal{B}_{21}(s) = b_{21}s^3, \quad b_{21} \in [-1, 0]
\end{aligned}$$

Let $\mathcal{D}(s) = K_d s^3 + K_p s^2 + K_r$, then

$$\mathcal{D}(s) = \{(d_{ij}(s)) : d_{ij}(s) \in \mathcal{D}_{ij}(s)\},$$

where

$$\mathcal{D}_{ij}(s) = \{d_{ij}(s) = k_{dij}s^2 + k_{pij}s + k_{rij}\}$$

and k_{dij}, k_{pij} and k_{rij} are given in (12). Thus, the characteristic polynomial of the uncertain system is

$$T(\epsilon) = \det(B(s)A(s) + D(s)); \quad B(s) \in \mathcal{B}(s), \quad D(s) \in \mathcal{D}(s) \tag{13}$$

where $A(s)$ is a fixed matrix and $\mathcal{B}(s), \mathcal{D}(s)$ are interval polynomial matrices.

The Kharitonov polynomial vertex sets associated with $\mathcal{B}_{ij}(s)$ and $\mathcal{D}_{ij}(s)$ are as follows,

$$\begin{aligned}
\mathcal{B}_{11}^V(s) &= \{s^3\} = \mathcal{B}_{11}(s), \quad \mathcal{B}_{12}^V(s) = \{s^3, 2s^3\}, \\
\mathcal{B}_{21}^V(s) &= \{-s^3, 0\}, \quad \mathcal{B}_{22}^V(s) = \{s^3\} = \mathcal{B}_{22}(s), \\
\mathcal{D}_{ij}^V(s) &= \left\{ \begin{aligned} d_{ij}^{(1)} &= K_{dij}^U s^2 + K_{pij}^L s + K_{rij}^L, & d_{ij}^{(2)} &= K_{dij}^U s^2 + K_{pij}^U s + K_{rij}^L, \\ d_{ij}^{(3)} &= K_{dij}^L s^2 + K_{pij}^L s + K_{rij}^U, & d_{ij}^{(4)} &= K_{dij}^L s^2 + K_{pij}^U s + K_{rij}^U, \end{aligned} \right\}
\end{aligned}$$

where the upper bound and the lower bound of K_{dij} are denoted as K_{dij}^U, K_{dij}^L . And the Kharitonov

edge sets associated with $\mathcal{B}(ij)$ and $\mathcal{D}(ij)$ are as follows.

$$\begin{aligned}\mathcal{B}_{11}^E(s) &= \{s^3\} = \mathcal{B}_{11}(s), \\ \mathcal{B}_{12}^E(s) &= \{\lambda s^3 + (1 - \lambda) \cdot 2s^3 : \lambda \in [0, 1]\}, \\ \mathcal{B}_{21}^E(s) &= \{-\lambda s^3 : \lambda \in [0, 1]\}, \\ \mathcal{B}_{22}^E(s) &= \{s^3\} = \mathcal{B}_{22}(s) \\ \mathcal{D}_{ij}^E(s) &= \left\{ \begin{array}{cc} \lambda d_{ij}^{(1)} + (1 - \lambda)d_{ij}^{(2)}, & \lambda d_{ij}^{(2)} + (1 - \lambda)d_{ij}^{(4)} \\ \lambda d_{ij}^{(4)} + (1 - \lambda)d_{ij}^{(3)}, & \lambda d_{ij}^{(3)} + (1 - \lambda)d_{ij}^{(1)} \end{array} \right\}\end{aligned}$$

By Proposition 1 given by Kamal and Dehleh, for any ϵ , $T(\epsilon)$ is robustly stable if and only if $T(\epsilon)$ is stable for all $B(s) \times D(s) \in \mathcal{B}_E \mathcal{D}_E$, where

$$\begin{aligned}\mathcal{B}_E \mathcal{D}_E &= U_1 \cup U_2 \\ U_1 &= \left(\begin{array}{cc} \mathcal{B}_{11}(s) & \mathcal{B}_{12}^E(s) \\ \mathcal{B}_{21}^E(s) & \mathcal{B}_{22}(s) \end{array} \right) \times \left(\begin{array}{cc} \mathcal{D}_{11}^V(s) & \mathcal{D}_{12}^E(s) \\ \mathcal{D}_{21}^E(s) & \mathcal{D}_{22}^V(s) \end{array} \right) \\ U_2 &= \left(\begin{array}{cc} \mathcal{B}_{11}(s) & \mathcal{B}_{12}^E(s) \\ \mathcal{B}_{21}^E(s) & \mathcal{B}_{22}(s) \end{array} \right) \times \left(\begin{array}{cc} \mathcal{D}_{11}^E(s) & \mathcal{D}_{12}^V(s) \\ \mathcal{D}_{21}^V(s) & \mathcal{D}_{22}^E(s) \end{array} \right)\end{aligned}$$

So, the robust stability of $T(\epsilon)$ is reduced to $2 \cdot 4^6$ robust stability problems involving four parameters. In this case, the testing set is a four-dimensional set. In the sequel, we apply Theorem 1 to simplify this problem further. That is to say, $T(\epsilon)$ is robustly stable if and only if $T(\epsilon)$ is stable for all $B(s) \times D(s) \in \mathcal{BD}$, where

$$\begin{aligned}\mathcal{BD} &= V_1 \cup V_2 \cup V_3 \cup V_4 \cup V_5 \cup V_6 \cup V_7 \\ V_1 &= \left(\begin{array}{cc} \mathcal{B}_{11}(s) & \mathcal{B}_{12}^E(s) \\ \mathcal{B}_{21}^E(s) & \mathcal{B}_{22}(s) \end{array} \right) \times \left(\begin{array}{cc} \mathcal{D}_{11}^V(s) & \mathcal{D}_{12}^V(s) \\ \mathcal{D}_{21}^V(s) & \mathcal{D}_{22}^V(s) \end{array} \right) \\ V_2 &= \left(\begin{array}{cc} \mathcal{B}_{11}(s) & \mathcal{B}_{12}^E(s) \\ \mathcal{B}_{21}^V(s) & \mathcal{B}_{22}(s) \end{array} \right) \times \left(\begin{array}{cc} \mathcal{D}_{11}^V(s) & \mathcal{D}_{12}^V(s) \\ \mathcal{D}_{21}^V(s) & \mathcal{D}_{22}^E(s) \end{array} \right) \\ V_3 &= \left(\begin{array}{cc} \mathcal{B}_{11}(s) & \mathcal{B}_{12}^E(s) \\ \mathcal{B}_{21}^V(s) & \mathcal{B}_{22}(s) \end{array} \right) \times \left(\begin{array}{cc} \mathcal{D}_{11}^V(s) & \mathcal{D}_{12}^V(s) \\ \mathcal{D}_{21}^E(s) & \mathcal{D}_{22}^V(s) \end{array} \right) \\ V_4 &= \left(\begin{array}{cc} \mathcal{B}_{11}(s) & \mathcal{B}_{12}^V(s) \\ \mathcal{B}_{21}^E(s) & \mathcal{B}_{22}(s) \end{array} \right) \times \left(\begin{array}{cc} \mathcal{D}_{11}^V(s) & \mathcal{D}_{12}^E(s) \\ \mathcal{D}_{21}^V(s) & \mathcal{D}_{22}^V(s) \end{array} \right) \\ V_5 &= \left(\begin{array}{cc} \mathcal{B}_{11}(s) & \mathcal{B}_{12}^V(s) \\ \mathcal{B}_{21}^E(s) & \mathcal{B}_{22}(s) \end{array} \right) \times \left(\begin{array}{cc} \mathcal{D}_{11}^E(s) & \mathcal{D}_{12}^V(s) \\ \mathcal{D}_{21}^V(s) & \mathcal{D}_{22}^V(s) \end{array} \right) \\ V_6 &= \left(\begin{array}{cc} \mathcal{B}_{11}(s) & \mathcal{B}_{12}^V(s) \\ \mathcal{B}_{21}^V(s) & \mathcal{B}_{22}(s) \end{array} \right) \times \left(\begin{array}{cc} \mathcal{D}_{11}^E(s) & \mathcal{D}_{12}^V(s) \\ \mathcal{D}_{21}^V(s) & \mathcal{D}_{22}^E(s) \end{array} \right) \\ V_7 &= \left(\begin{array}{cc} \mathcal{B}_{11}(s) & \mathcal{B}_{12}^V(s) \\ \mathcal{B}_{21}^V(s) & \mathcal{B}_{22}(s) \end{array} \right) \times \left(\begin{array}{cc} \mathcal{D}_{11}^V(s) & \mathcal{D}_{12}^E(s) \\ \mathcal{D}_{21}^E(s) & \mathcal{D}_{22}^V(s) \end{array} \right)\end{aligned}$$

Clearly, the robust stability of $T(\epsilon)$ is reduced to $7 \cdot 4^6$ robust stability problems involving two parameters. In this case, the minimal testing set is two-dimensional.

Remark 4: A test with one uncertain parameter could involve infinite tests, e.g., an edge contains infinite points. The significance of our result is that it is the minimal dimension test for such problem (1). Although the number of robust stability problem is slightly increased, the dimension of the testing set is significantly reduced. Furthermore, we considered the uncertainty in inertia matrix $M(\theta_d)$ in the above Example, whereas Kamal and Dahleh did not take into account [8].

5 Discussions

The focal point of this paper is to establish a lower dimensional robust stability criterion for robust-

ness of multivariable control systems. By improving the result given by Kamal and Dahleh, we have significantly reduced the high-dimensional stability verification problem to a much lower-dimensional problem in parameter space, e.g., for a 2×2 interval control system family, our result reduces 8-dimensional robust problem to a 2-dimensional one and Dahleh's result reduced this an 8-dimensional robust problem to a 4-dimensional one. Furthermore, when dealing with SISO systems, our result naturally reduces to the well-known Box Theorem. Of course, from the computational viewpoint, checking robust D -stability of interval polynomial matrices is NP-hard. Hence, some sufficient (conservative) conditions were developed based on linear matrix inequality(LMI) techniques. And how to reduce the conservativeness of these conditions is still under investigations. on the other hand, from the theoretical viewpoint, establishing lower-dimensional necessary and sufficient condition for robust D -stability of interval polynomial matrices is important as well. By our result, the 'nucleus' of the uncertainty structures can be identified, which is very useful in dealing with robust performance of control systems under structured parametric perturbations^{[1]–[12]}.

6 Conclusions

In this paper, robustness of MIMO control systems with interval transfer function matrices is studied. For a family of multivariable control systems having interval transfer functions matrices, a lower dimensional robust stability criterion has been established. This result improves the previous criterion obtained by Kamal and Dahleh, and can be used to establish improved lower dimensional robust performance criteria as well.

Acknowledgements

This work was supported by National Natural Science Foundation of China (10372002, 60204006 and 69925307), the Knowledge Innovation Pilot Program of the Chinese Academy of Sciences, National Key Basic Research and Development Program (No. 2002CB312200).

References

- [1] V. L. Kharitonov. Asymptotic stability of an equilibrium position of a family of systems of linear differential equations, *Differential'nye Uravneniya*, vol.14, 2086-2088, 1978.
- [2] A. C. Bartlett, C. V. Hollot and L. Huang. Root locations of an entire polytope of polynomials: It suffices to check the edges, *Mathematics of Control, Signals, and Systems*, vol.1, 61-71, 1988.
- [3] S. P. Bhattacharyya, H. Chapellat and L. H. Keel. *Robust Control: The Parametric Approach*. Prentice Hall PTR, Upper Saddle River, NJ, 1995.
- [4] S. Bialas. A necessary and sufficient condition for the stability of interval matrices, *Int. J. Control*, vol.37, 717-722, 1983.
- [5] B. R. Barmish and C. V. Hollot. Counter-example to a recent result on the stability of interval matrices by S. Bialas, *Int. J. Control*, vol.39, 1103-1104, 1984.
- [6] H. Kokame and T. Mori. A Kharitonov-like theorem for interval polynomial matrices, *Systems and Control Letters*, vol.16, 107-116, 1991.
- [7] L. Wang, Z. Wang and W. S. Yu. Stability of polytopic polynomial matrices. *Proc. of American Control Conference*, Arlington, Virginia, June: 4695-4696, 2001.

- [8] F. Kamal and M. Dahleh. Robust stability of multivariable interval control systems, *Int. J. Control*, vol.64, 807-828, 1996.
- [9] L. Wang. Robust stability of a class of polynomial families under nonlinearly correlated perturbations, *Systems and Control Letters*, vol.30, 25-30, 1997.
- [10] J. Ackermann, *Robust Control: Systems with Uncertain Physical Parameters*. Springer-Verlag, London, 1993.
- [11] B. R. Barmish, New tools for robustness analysis, *Proc. of IEEE Conf. on Decision and Control*, 1-6, 1988.
- [12] Z. Wang, L. Wang, W. Yu and G. Liu, Improved results on robust stability of multivariable interval control systems, *Proc. of American Control Conference*, Denver, CO., USA, June, 4463-4468, 2003.